

## VoIP Voicemail Initialization

To initialize a new voicemail box:

1. Decide on a four (4) or five (5) digit password
2. Pick up the handset and dial:
  - a. \*98 – This is the voicemail access code
  - b. Your two digit city code. See the chart below
  - c. Your three digit extension number
  - d. The pound sign (#).
  - e. Example, for Durant extension 123, dial \*98-38-123-#
3. When the system prompts “password”, enter the default password, 1 2 3 4.
4. Press 0 for mailbox options.
5. There are 3 items you should record:
  - a. 1 – Unavailable message. This is the message callers will hear when you do not answer their call. Press 1 and follow the voice prompts to record and approve.
  - b. 2 – Busy message. This is the message callers will hear when you are already on the phone and do not answer their call. Press 2 and follow the voice prompts to record and approve.
  - c. 3 – Name. Simply record your name to personalize your messages. Press 3 to record and approve.
6. Press 5 and dial your new password at the prompt followed by the pound sign (#).
7. Confirm your new password by reentering it and pressing the number sign (#).
8. You can start over anytime by hanging up and beginning with step 2.
9. The system is setup to e-mail your message to you. Also, the blinking red light on the phone and the stuttered dial tone indicate you have messages. Dial \*98-[City Code]-[Extension]-# to retrieve or erase your messages from any VoIP phone.
10. Alternately, GXP2140 phones can access voicemail by pressing the envelope button.

City Codes:

|            |    |
|------------|----|
| Ardmore    | 27 |
| Atoka      | 28 |
| Boswell    | 26 |
| Broken Bow | 22 |
| Brownwood  | 29 |
| Durant     | 38 |
| Hugo       | 48 |
| Sherman    | 74 |